



BATTERY CHARGERS



Innovation

for
better

control



BATTERY CHARGERS

Innovation for better control

CRE TECHNOLOGY's range of battery chargers is designed to supply voltage to the battery with a permanent connection and a maximum of efficiency.

4 RANGES

The BP305+, Compact, BP and the BPRB series are available:

- From 3A to 40A in 12V_{DC} or 24V_{DC}
- Single or three-phase input, all chargers support 50Hz and 60Hz
- Voltage input range from 85V_{AC} to 550V_{AC}

BP+ 305 RANGE - FROM 3A TO 10A

The BP+ battery chargers range offers a range of input voltages in monophase, a range of output current from **3A to 10A** and voltage output from **12V_{DC} to 24V_{DC}**. They integrate a permanent short-circuit protection and accept without damage the electrical starters inrush current. Their ergonomic design allows you to easily integrate it into your plant thanks to their lightness, compactness and Din Rail support.

- With Diode integrated
- Can be installed on DIN Rail
- Competitive price



BP+ 0512M305-



BP+ 0324M305-



BP+ 1012M305-



BP+ 0524M305-



BP+ 1024M305-

REFERENCES	OUTPUT CURRENT	OUTPUT VOLTAGE	DC VOLTAGE ADJUSTABLE	INPUT VOLTAGE RANGE	INPUT FREQUENCY RANGE	EFFICIENCY (TYPICAL)	WORKING TEMPERATURE	STORAGE TEMPERATURE	WIDTH	HEIGHT	DEPTH	WEIGHT	FAILURE RELAY	BOOST MODE (ACTIVATED BY EXTERNAL CONTACT)
UNIT	A	V _{DC}	-	V _{AC}	Hz	%	°C	°C	mm	mm	mm	kg	-	
BP+ 305 RANGE														
BP+ 0512M305-	5	15 - 12	Yes	305 ~ 90	63 - 47	83	70+ / 20-	85+ / 40-	32	125.2	102	0.51	No	No
BP+ 0324M305-	3	28 - 24	Yes	305 ~ 90	63 - 47	87	70+ / 20-	85+ / 40-	32	125.2	102	0.51	No	No
BP+ 1012M305-	10	28-24	Yes	305 ~ 90	63 - 47	84	70+ / 20-	85+ / 40-	40	125.2	113.5	0.57	No	No
BP+ 0524M305-	5	28 - 24	Yes	305 ~ 90	63 - 47	87	70+ / 20-	85+ / 40-	40	125.2	113.5	0.57	No	No
BP+ 1024M305-	10	28 - 24	Yes	305 ~ 90	63 - 47	87	70+ / 20-	85+ / 40-	63	125.2	113.5	1	No	No

COMPACT RANGE - FROM 3A TO 10A

CRE TECHNOLOGY range of battery chargers Compact serie has been designed to supply constant voltage to the battery with a permanent connection and a maximum of efficiency.

- Protection: Short circuit/ Overload/ Over voltage
- LED indicator for power on
- Cooling by free air convecti on
- Can be installed on DIN rail TS7.5/35- or TS15/35-
- FAULT contact, no load power consumpti on <0.75W
- %100 full load burn-in test
- 3 years warranty



BPR0324S
MULTIANGLE VIEW

REFERENCES	OUTPUT CURRENT	OUTPUT VOLTAGE	DC VOLTAGE ADJUSTABLE	INPUT VOLTAGE RANGE	INPUT FREQUENCY RANGE	EFFICIENCY (TYPICAL)	WORKING TEMPERATURE	STORAGE TEMPERATURE	WIDTH	HEIGHT	DEPTH	WEIGHT	FAILURE RELAY	BOOST MODE (ACTIVATED BY EXTERNAL CONTACT)
UNIT	A	V _{DC}	-	V _{AC}	Hz	%	°C	°C	mm	mm	mm	kg	-	
COMPACT RANGE														
BPR 0324S	2.5	28 - 24	Yes	264~ 85	63 - 47	88	70+ / 20-	85+ / 40-	40	90	100	0.33	Yes	No
BPR 0512S	5	15 - 12	Yes	264 ~ 85	63 - 47	88	70+ / 20-	85+ / 40-	40	90	100	0.33	Yes	No

BATTERY CHARGERS

Innovation for better control

BPRB RANGE - FROM 2A TO 20A

The **BPRB SERIES** offers a wide range of input voltages, a wide range of output current from **5A to 20A** and voltage output from **12V_{DC} to 24V_{DC}**. Their ergonomic design allows you to easily integrate it into your plant thanks to their lightness, compactness and Din Rail support. Included a Fail Output Relay, and a **Boost Mode** Input.

- Protections: Short circuit/ Overload/ Over voltage/ Over temperature
- Boost mode (connector and wires provided)
- Cooling by free air convection
- Can be installed on DIN rail TS7.5/35- or TS15/35-
- Fault relay contact
- %100 full load burn-in test
- 3 years warranty



BPRB 0524 M
BOOST MODE



BPRB 1012 M
BOOST MODE



BPRB 1024 M
BOOST MODE



BPRB 2024 M
BOOST MODE

REFERENCES	OUTPUT CURRENT	OUTPUT VOLTAGE	DC VOLTAGE ADJUSTABLE	INPUT VOLTAGE RANGE	INPUT FREQUENCY RANGE	EFFICIENCY (TYPICAL)	WORKING TEMPERATURE	STORAGE TEMPERATURE	WIDTH	HEIGHT	DEPTH	WEIGHT	FAILURE RELAY	BOOST MODE (ACTIVATED BY EXTERNAL CONTACT)
UNIT	A	V _{DC}	-	V _{AC}	Hz	%	°C	°C	mm	mm	mm	kg	-	-

BPRB RANGE

BPRB 0524M	5	29 - 24	Yes	550 ~ 180	63 - 47	91	70+ / 25-	85+ / 40-	40	125.2	113.5	0.65	Yes	Yes
BPRB 1012M	10	15 - 12	Yes	550 ~ 180	63 - 47	89.5	70+ / 25-	85+ / 40-	40	125.2	113.5	0.65	Yes	Yes
BPRB 1024M	10	28 - 24	Yes	550 ~ 180	63 - 47	90	70+ / 25-	85+ / 40-	63	125.2	113.5	1	Yes	Yes
BPRB 2024M	20	28 - 24	Yes	550 ~ 180	63 - 47	91	70+ / 25-	85+ / 40-	85.5	125.2	128.5	1.7	Yes	Yes

BP RANGE - FROM 20A TO 40A

The BP battery chargers range offers a wide range of input voltages in monophase or three-phase, a wide range of output current from **5A to 40A** and voltage output from **12V_{DC} to 24V_{DC}**. They integrate a permanent short-circuit protection and accept without damage the electrical starters inrush current. Their ergonomic design allows you to easily integrate it into your plant thanks to their lightness, compactness and Din Rail support.

- AC input range selectable by switch
- Protections: Short circuit/ Overload/ Over voltage/ Over temperature
- Cooling by free air convection, LED indicator for power on
- Can be installed on DIN rail TS7.5/35- or TS15/35-
- %100 full load burn-in test
- Fixed switching frequency at 55kHz (120kHz for BP1024M)
- 3 years warranty



BP 2024 M



BP 2024 T
TREEPHASE



BP 4024 T
TREEPHASE

REFERENCES	OUTPUT CURRENT	OUTPUT VOLTAGE	DC VOLTAGE ADJUSTABLE	INPUT VOLTAGE RANGE	INPUT FREQUENCY RANGE	EFFICIENCY (TYPICAL)	WORKING TEMPERATURE	STORAGE TEMPERATURE	WIDTH	HEIGHT	DEPTH	WEIGHT	FAILURE RELAY	BOOST MODE (ACTIVATED BY EXTERNAL CONTACT)
UNIT	A	V _{DC}	-	V _{AC}	Hz	%	°C	°C	mm	mm	mm	kg	-	-

BP RANGE

BP 2024M	20	28 - 24	Yes	264 ~ 180	63 - 47	89	70+ / 20-	85+ / 20-	227	125.2	100	2.4	No	No
BP 2024T	20	28 - 24	Yes	550 ~ 304 phase-to-phase	63 - 47	89	70+ / 20-	85+ / 40-	227	125.2	100	2.5	No	No
BP 4024T	40	28 - 24	Yes	550 ~ 304 phase-to-phase	63 - 47	91	60+ / 20-	85+ / 40-	276	125.2	100	3.3	No	No



Local Partner

CRE TECHNOLOGY - 130, allée Charles-Victor Naudin -
Zone des Templiers - SOPHIA ANTIPOLIS - 06410 BIOT - FRANCE
Phone : + 33 (0)4 .92.38.86.82 -
www.cretechnology.com - info@cretechnology.com

Office No:
501 , Makkah Tower, King Abdullah Road, Makkah
Street Crossing PO Box : 4160, Al Khobar 31952
Kingdom of Saudi Arabia + 966 (13) 8642040
info@anjamgroup.com www.anjamgroup.com